

# DATA SHEET SPECIFICATION

## UPG-P1000

50 Hz



Genset Model

UPG-P1000

Engine Model

Perkins 4008-TAG2A

Alternator Model

TAL 049 E

Controller Model

DSE 7320



### Dimension

Closed type(mm)		Open type(mm)	
Length	6000	Length	4900
Width	2320	Width	1870
Height	2790	Height	2300
Weight(kg)	10550	Weight(kg)	7550

### POWERED BY



**T** Three phase **W** water cooled

**D** DIESEL **B** Battery Charging Alternator

### Ratings @ 0.8 PF

VOLTAGE	FREQUENCY	PRIME RATING		STAND-BY RATING	
		1000 kva	800 kw	1125 kva	900 kw
230-400 V	50 Hz				

### Prime

These ratings are applicable for supplying continuous electrical power (at variable load). There is no annual hours limitation and this genset can supply 10% overload for 1 hour in 12 hours

### Stand by

These ratings are applicable for supplying continuous electrical power(at variable load) in the case of emergency power supply. No overload is permitted on the ratings.  
The alternator on this model is peak continuous rates(as defined in ISO 8528-5)

Some of the specifications are not standard on all Genset models.

### Genset Standard Specification

Model	UPG-P1000
Base frame	Heavy duty fabricated steel
Circuit breaker	ABB 3 pole MCCB.(4 pole is optional)
Engine speed	1500 RPM(50HZ)
Fuel tank capacity	Not available*
Air inlet	Mounted air filter
Induction system	Turbo charged and air to air charge cooled
Combustion system	Direct injection
Fuel system	Fuel injection pump
Fuel filter	Split element
cooling system	Water-cooled
Electric Equipment	24 v starter motor and 24 v DC alternator and ECM

\* Base tank not recommended for above 800 kva genset for sufficient cooling of diesel

All information in this document is substantially correct at time of printing and may be altered subsequently.

### Engine Data

Model	Perkins 4008-TAG2A	
No of cylinder & arrangement	8 vertical in-line	
Compression ratio	13.6:1	
Aspiration	Naturally Aspirated	
Bore and stroke(mm)	160*190	
Rotation	Anti-clockwise viewed from flywheel end	
Governing class	ISO 3046-1 Part 4 class A1	
Radiator cooling air flow(m <sup>3</sup> /sec)	0.04	
	50 Hz	
	Prime	Stand by
Gross engine power kw(hp)	901 (1208)	997(1298)
at 75% Load(l/hr)	160	-
at 50% Load(l/hr)	108	-
at 100% Load(l/hr)	213	234
Boost pressure ratio	3.4	3.86
Total lubrication system capacity(L)	153	153
Total Coolant capacity(L)	140	140

### Alternator Data

Make	Leroy Somer TAL / Equivalent
Model	TAL 049 E
Insulation class	H
No of bearing	1
Total harmonic content	at no load<3.5%at linear load<5%
Winding pitch	2/3
Ingress Protection	IP23
Altitude	≤1000m
Overspeed	2250 R.P.M
AVR Model	R150
Excitation system	SHUNT
Voltage regulation(steady)	±1%

AREP or PMG Excitation System Available as Optional

Exhaust pipes with exhaust heat



Oil and coolant drain



Anti-vibration pads



Fuel Inlet/Outlet



Emergency stop button



## Enclosure

### SILENT FEATURES:

- Lockable external fuel filling point
- Internal /External fuel connection
- External oil drainage
- External coolant drainage
- Air inlet /outlet louvers
- Sound splitters at radiator side (only for 1000 KVA and above) (For 725-880 KVA vertical air discharge)
- Common earth connection
- 2 layers white color paint
- Cooling fan and battery charging alternator fully guarded
- Engine, radiator, fuel fill and battery can only be reached via lockable access doors

### HIGLY CORROSION RESISTANCE CONSTRUCTION

- Carbon steel locks and hinges
- Body made from galvanized steel components (2.0mm) treated with polyester powder coating

### TRANSPORTABILITY

- Tested and certified single point lifting facility
- Forklift legs available

### SOUND PRESSURE LEVEL

- 80 - 85 dBA at 3 meters (standard)

### SECURITY AND SAFETY:

- Control panel viewing window in a lockable access door
- Emergency stop push button (red) fixed externally for quick access
- Cooling fan and battery charging alternator fully guarded
- Fuel fill and battery can only be reached via lockable access doors
- Exhaust silencing system totally enclosed for operator safety

### Control Panel Data

Make	Deep Sea
Model	DSE 7320 MKII



## Controller key features

The DSE 7320 is an Auto Start Control Module for single genset applications. It includes a backlit LCD display which clearly shows the status of the engine all the times. This module can either be programmed using the front panel or by using the DSE configuration suite PC software.

### Metering and Alarm indications:

- Generator frequency
- Underspeed, Overspeed
- Generator volts (L-L, L-N)
- Generator current
- Engine oil pressure
- Engine coolant temperature
- Fuel level (Warning or shutdown) - Optional
- Hours run counter
- Battery volts
- Fail to start/stop
- Emergency stop
- Failed to reach loading voltage/frequency
- Charge fail
- Loss of magnetic pick-up signal - Optional
- Low DC voltage
- CAN diagnostics and CAN fail/error

### FUEL SYSTEM

On Generating Sets up to 700 KVA, the baseframe design is incorporated with an integral fuel tank with a capacity of approx. 8 hours running at Full Load. The tank is supplied complete with fill cap breather, fuel feed and return lines to the Engine and drain plug.

Max allowable pressure	50 Hz
Kpa	8
Exhaust gas flow m <sup>2</sup> /min	50 Hz
Prime	185
Standby	203
Exhaust gas temperature °C	50 Hz
Prime	462
Stand by	475

### AUTOMATIC VOLTAGE REGULATOR (AVR)

The fully sealed Automatic Voltage Regulator maintains the Voltage Regulation at ±1%. Nominal adjustment by means of a trim pot incorporated on the AVR.

### MOTOR STARTING

An overload capacity equivalent to 300% of the Full Load impedance at zero Power Factor can be sustained for 10 seconds, when PMG option is fitted.

### COUPLING

The Engine and Alternator are directly coupled by means of an SAE flange. The Engine flywheel is flexibly coupled to the Alternator rotor.

### ANTI-VIBRATION MOUNTING PADS

Anti-Vibration pads are affixed between the Engine / Alternator feet and the Baseframe thus ensuring complete vibration isolation of the rotating assembly.

### SAFETY GUARDS

The Fan & Fan Drive along with the Battery Charging Alternator are Safety Guard protected for personnel protection.

### FACTORY TESTS

The Generating set is load tested before dispatch All protective devices control functions and site load conditions are simulated. The generator and it's systems are checked before dispatch.

## DOCUMENTATIONS

Operation & Maintenance manual, Circuit wiring diagrams and Commissioning / Fault Finding accompanied with the Generator.

## QUALITY STANDARDS

Following standards: ISO 8528/1, ISO 3046/1, BS 5514/1.

## WARRANTY

All of the Generating Sets are covered under a warranty policy for a period of 12 months. Warranty of the equipment is in line with manufacturers warranty terms & conditions.

All information in this document is substantially correct at time of printing and may be altered subsequently.